

**CE120****Controller**

**Electronic controller with fully adjustable control blocks for control of TecEquipment's Control Engineering (CE) range**



- Compact, bench-mounting unit that includes easy-to-connect blocks of all the important parts of a process controller
- All inputs and outputs are low voltage and buffered for educational use
- Includes proportional, integral and PID blocks and summing junctions
- Includes an interface for computer control (with data acquisition) of TecEquipment's Control Engineering range
- Front panel has clear diagrams that mimic parts of the controller, so students can see and understand what they connect
- Supplied with TecEquipment's Control Software (CE2000) for control and data acquisition
- Includes digital meter to measure voltages and show the frequencies from the on-board function generator

**Description**

The CE120 Controller is for use with most products in TecEquipment's Control Engineering range, but it will work with any other compatible laboratory equipment.

It is a mains-powered compact unit with electronic circuits connected in blocks. These blocks mimic the important parts of industrial controllers. Clear diagrams on the front panel of the controller show the blocks and each block has its own set of connection sockets. The user connects the blocks in any way that they need and then connects them to their chosen products in the CE range.

The blocks include:

- Proportional and integral blocks
- A complete three-term PID (proportional, integral, derivative) block
- Fully adjustable potentiometers that can work as set-points or attenuators
- A function generator and digital voltmeter
- Summing junctions
- Phase lead

The controller also includes an interface with D/A (digital to analogue) and A/D (analogue to digital) connections. This allows the user to connect their product from the CE range to a suitable computer (not supplied) for computer control and data acquisition. Supplied with the CE120 is TecEquipment's CE2000 Control Software (see separate datasheet for details).

The Controller is an alternative to the CE122 Interface, but with the additional hardware controller features.

- TecEquipment Ltd, Bonsall Street, Long Eaton, Nottingham NG10 2AN, UK
- **T** +44 115 972 2611 • **F** +44 115 973 1520 • **E** info@tecquipment.com • **W** www.tecquipment.com
- An ISO 9001 certified company

# CE120

# Controller

## Standard Features

- Supplied with comprehensive user guide
- Two-year warranty
- Made in accordance with the latest European Union directives

## Experiments

When used with other products in the CE range:

- Temperature (thermal) control
- Level control
- Engine speed control
- Servo control
- Coupled drive control
- Ball and beam control
- Ball and hoop control

## Recommended Ancillaries

- Suitable computer with two spare USB connections (not supplied by TecEquipment) – see the CE2000 datasheet for full details.
- Selected products in TecEquipment's Control Engineering range:
  - CE103 Thermal Process Control
  - CE105 and CE105 MV Coupled Tanks
  - CE106 Ball and Beam
  - CE107 Engine Speed Control
  - CE108 Coupled Drives
  - CE109 Ball and Hoop
  - CE110 Servo Trainer
  - CE117 Process Trainer

## Essential Services

### Electrical supply:

240/110 VAC, 1 A, 50/60 Hz, with earth

Other voltages and frequencies available to special order

### Bench space needed:

800 mm x 600 mm

## Operating Conditions

### Operating environment:

Laboratory environment

### Storage temperature range:

-25°C to +55°C (when packed for transport)

### Operating temperature range:

+5°C to +40°C

### Operating relative humidity range:

80% at temperatures < 31°C decreasing linearly to 50% at 40°C

## Sound Levels

Less than 70 dB(A)

## Specifications

### Nett dimensions and weight:

540 x 330 x 140 mm, 10 kg

### Packed dimensions and weight:

0.18 m<sup>3</sup>, 20 kg (approx – packed for export)

### Summing junctions:

Four, each with three '+ve' inputs and one '-ve' input.

### Integrators:

Three, each with variable gain

### Proportional amplifiers:

Four, each with variable gain

### PID block:

Parallel connected proportional, integral and derivative block – each part has variable gain

### Potentiometers and power supply:

- Four potentiometers for general-purpose applications, such as adjusting the 'set points' or attenuating a signal
- +10 VDC, 0 V and -10 VDC power supply

### Display and function generator:

Digital display of voltage measured (+/- 15 V) or frequency of function generator. Function generator gives square, sinusoidal or sawtooth signals at variable frequency. Signals can be offset and amplitude adjusted. Frequency range 0.01 to 100 Hz

### Phase lead block:

One, with three settings

### Interface:

- Eight A-D inputs: ±10 V
- Four D-A outputs: ±10 V,
- USB connection to suitable computer